



NICOPRESS[®] SPLICING SLEEVES FOR RAILROAD TRACK SIGNAL CABLES

Stock Number	Conductors		Sleeve Length	Weight Lbs./M Pieces	Tool Groove
	From:	To:			
1792-B	#14 STR COP & #14 SOL COP	#14 STR COP & #14 SOL COP	1-1/8"	2	17-2
2314-J	3/16" & 13/64" - 7 x 19 BRONZE ALSO: #6-#7 STR SOFT COPPER	#9 OR #10 SOLID COPPER	1-3/8"	27	J
2363-J	SAME AS ABOVE	#6 SOL & #8 (7 or 19 STR COPPER	1-3/8"	25	J
2364-J	SAME AS ABOVE	#8 SOLID COPPER	1-3/8"	26	J
2367-J	SAME AS ABOVE	#6 - 7 COPPER	1-1/2"	24	J
2412-J•	3/16" & 13/64" - 7 x 19 BRONZE	1/4" BINDING POST	1-1/8"	15	J
2342-J (S)•	3/16" - 7 x 19 BRONZE	1/4" BINDING POST	1-1/2"	22	J
2738-J (S)	3/16" & 13/64" - 7 x 19 BRONZE	#9 STRANDED COPPER	1-3/8"	26	J
2770-J (S)	3/16" & 13/64" - 7 x 19 BRONZE	3/16" & 13/64" - 7 x 9 BRONZE		43	J
92-162/7-J†	#6-7 STRANDED COPPER	#6-7 STRANDED COPPER		43	J
1782-M	1/4" FLEXIBLE STEEL STR	#9 SOLID COPPER	2-1/8"	58	M
2054-M	13/64" - 7 x 19 STR COP or #4 SOL COP	#9 SOLID COPPER	2-1/8"	62	M
1302	1/4" - 7 STR COPPERWELD	#8 SOLID COPPER	2-1/8"	75	P
2109	1/4" - 7 STR COPPERWELD	1/4" - 7 STR COPPERWELD	2-1/8"	60	P
1237	5/16" - 7 STR COPPERWELD	5/16" - 7 STR COPPERWELD	2-1/8"	88	X
1583	5/16" - 7 STR COPPERWELD	#6 SOLID COPPER	2-1/8"	97	X
3701-P	3/16" - 7 X 19 BRONZE	#4-7 STR COPPER	2"		

• = Compression Terminal † = Off-Set Dead End
(S) = Contact Factory for Price and/or Availability